

Digital Multimeter

Protek 9902A



■ Features

- AC / DC Voltage, AC / DC Current, Resistance Measurement
- 4 1/2 Digit Display
- Over Range Indication
- 7 Functions
- Data Hold Function

■ Specifications

| | | | | | | |
|------------|-------------------|---------------------------------|-------|------|-------|-------|
| DC Voltage | Range | 200mV | 2V | 20V | 200V | 1000V |
| | Resolution | 10µV | 100µV | 1mV | 10mV | 100mV |
| | Accuracy | $\pm (0.05\% \text{rdg} + 2d)$ | | | | |
| AC Voltage | Range | 200mV | 2V | 20V | 200V | 750V |
| | Resolution | 10µV | 100µV | 1mV | 10mV | 100mV |
| | Accuracy | $\pm (0.05\% \text{rdg} + 10d)$ | | | | |
| DC Current | Range | 200µA | 2mA | 20mA | 200mA | 10A |
| | Resolution | 10µA | 0.1µA | 1µA | 10µA | 1mA |
| | Accuracy | $\pm (0.3\% \text{rdg} + 3d)$ | | | | |
| AC Current | Range | 200µA | 2mA | 20mA | 200mA | 10A |
| | Resolution | 10mA | 0.1µA | 1µA | 10µA | 1mA |
| | Accuracy | $\pm (0.75\% \text{rdg} + 10d)$ | | | | |
| Resistance | Range | 200Ω | 2KΩ | 20KΩ | 200KΩ | 2MΩ |
| | Resolution | 10mΩ | 100mΩ | 1Ω | 10Ω | 100Ω |
| | Accuracy | $\pm (0.2\% \text{rdg} + 5d)$ | | | | |
| General | Power Requirement | 115V / 230V ± 10%, 50 / 60Hz | | | | |
| Dimension | | 250 (W) × 267 (D) × 76 (H) mm | | | | |
| Weight | | Approx. 2.5Kg | | | | |